

Quick Callshop Install Guide for Resellers

1 Create Callshop

After your free registration as a reseller at www.my-hostedcallshop.com you receive your username and password in your email. Now login at reseller.my-hostedcallshop.com.

At first you create your callshop: Click „CALLSHOP“ and „Add“. Enter callshop name, title, description, credit limit and Limit Type. When finished click „Continue“.

2 Create Login account for your callshop

Next step is to create login account for your callshop. Click „ACCOUNT“ and „Add“. Enter Username and Password for new callshop. Select User Type „Callshop Admin“ and select above created Callshop. Now click „Continue“. Your new callshop can now login with just created account at: callshop.my-hostedcallshop.com

3 Manage your selling rates to callshop

Next step is to create your selling rates to your callshop. Click „ADVANCED RATEMANAGEMENT“. Here you can select your previously created callshop and manage your selling rates. Click „Recalculate Rates“ for standard multiples and calculations, than choose „Edit Rates“ for individual rate change. When finished click „Save“ and „Finish“.

Sell rates

[Buy rates](#) [Sell rates](#) [Rates with calculations](#) [Recalculate rates](#) [Edit Rates](#) [Finish](#)

Reseller: Reseller-demo (id: 1) Callshop: New Callshop (id: 2489)

Prefix	Destination	Connect charge	Init Step	Bill step	Current Sell
0093	Afghanistan	0.0000	0	1	0.1920
00937	Afghanistan.Mobile.Others	0.0000	0	1	0.2262
00355	Albania	0.0000	0	1	0.0523

Recalculate rates

[Buy rates](#) [Sell rates](#) [Rates with calculations](#) [Recalculate rates](#) [Edit Rates](#) [Finish](#)

Reseller: Reseller-demo (id: 1) Callshop: [New Callshop (id: 2489)]

Digit size: 0.000 Round up to multiple of: Multiple of 2

Currency multiple: 1 Multiple buyrate with: 1.3

Add at least this amount: 0.01 Connect charge: 0

Init Step: 10 Bill step: 60

Show threshold for profit in percent: 27

Prefix	Destination	Buy		Current Sell			Future sell			Calculations				
		Buy (EUR)	Buy	Connect charge	Init Step	Bill step	Current Sell	Connect charge	Init Step	Bill step	Future sell	change	Profit	Profit % (sell=100%)
0093	Afghanistan	0.1000	0.1000	0.0000	0	1	0.1920	0	10	60	0.146	-0.046	0.0460	+31.51 %
00937	Afghanistan.Mobile.Others	0.1100	0.1100	0.0000	0	1	0.2262	0	10	60	0.158	-0.068	0.0480	+30.38 %
00355	Albania	0.0300	0.0300	0.0000	0	1	0.0523	0	10	60	0.054	+0.002	0.0240	+44.44 %

4a Create booth and SIP-accounts

Now you can create booth's for your callshop. Click „BOOTH“ and „Add“.

Here you can enter SIP-Username for this new booth, SIP-Password is created automatically. „Display“ will be shown as headline in booth interface, enter booth number or some description here. You can set Credit limit and Limit Type for each booth, but it is suggested to leave it at „No Limit“. Finally you select your previously defined Callshop and „Available“. Click „Continue“ to create this new booth. Repeat this procedure for each new booth. When finished click „generate sip peers“ and „reload sip peers“.

SIP-Username*	1234567890
SIP-Password*	6341538543
Display	New Booth A
Credit Limit	
Limit Type	No Limit
Reseller	Reseller-demo
Callshop	New Callshop
Status	Available

Continue

4b Configure your SIP-device

Now you can configure your SIP-devices, e.g. Linksys PAP.

Open Webinterface of your Linksys and click „Line 1“ for first SIP account to configure.

Proxy: sip.my-hostedcallshop.com

Enter above created SIP-Username into following 3 fields:
Display Name, UserID and AuthID

Enter above created SIP-Password in field „Password“ and save configuration.

Now your Linksys should become online. Please refer to manual of your SIP-device for further Information how to configure SIP-accounts.

LINKSYS®
A Division of Cisco Systems, Inc.

Phone Adapter with 2 Ports for Voice-Over-IP

Voice

Info System SIP Regional Line 1 Line 2 User 1 User 2

Basic View (switch to advanced view)

Line Enable: yes

SIP Port: 5060

Proxy: sip.my-hostedcall Register: yes

Make Call Without Reg: no Register Expires: 10

Ans Call Without Reg: no

Subscriber Information

Display Name: 1234567890 User ID: 1234567890

Password: 1203415684 Use Auth ID: yes

Auth ID: 1234567890

5 Management and Payments

Your callshop and booth's are ready for calls. Repeat above procedure for each new callshop

To manage payments or credit limits of your callshops, click „Callshop“ and Symbol „Edit“.

Dont forget to click „generate sip peers“ and „reload sip peers“ after you added a new booth.

You can list all payments at „Credit History“ and check your own balance at „Profile“.

Detailed reports are available at „Reports“.

If you need further assistance in starting your callshop reseller business feel free get in contact at our Support chat at www.my-hostedcallshop.com